E9762WW - 20w 240v Compact Floodlight with PIR Sensor - Black - IP64 - Warm White 1800lm - 3000K

Description

E9762WW Compact Tough PIR Floodlight is an adjustable 240v LED floodlight with a die-cast aluminium body and mounting bracket powder-coated in black. It has a high-efficiency 20w COB led providing a light output of 1800Lm and an even 110 degree beam perfect for security lighting.

Electrical	240v 3000K built in LED
Colour/ Finish	Black powder coated aluminium
Exterior Dimensions	Body 120mm wide x 157mm tall.



240v | Wide beam | IP64 | Built-in LED

Ensure that the power is OFF during installation and that power cannot be unexpectedly reconnected.
Place the light fitting on a stable surface and with an Allen key remove the U-bracket from the LED floodlight and store the retaining bolts, split-locks and washers (M6 bolts on 10W/20W and M8 bolts on 30W/50W).
Present the U-bracket to a suitable position and surface so that it can be mounted flush. Check with a
spirit level if required. Mark out two suitable fixing positions. Use suitable tools and fixings to mount the U-bracket safely and securely to the surface, depending on the substrate; alternative fixings to the items supplied may be required. We recommend using washers to fix the U-bracket. Avoid damage to any wiring. 2 X screws, wall plugs and washers supplied.
Once the U-bracket is mounted, securely reattach the LED floodlight ensuring it is the correct way up
and at the appropriate angle. Ensure bolts are tight on both sides of the U-bracket.
Connect the LED floodlight cable to a suitably protected waterproof junction box.

2 YEAR WARRANTY

Powder coated aluminium body & fitting

Exclusions: Damage by machinery, animals or the use of incorrect cleaning materials. Corrosion due to exposure to salt or chlorine. Damage due to incorrect installation practices. Responsibilty for 3rd party cost; indirect or consequential loss

